

Owners Guide – Underground Dog Fence

EcoLite™ Rechargeable Receiver & Invisible Fence Brand Compatible

Introduction - Only Rechargeable Commercial Dog Collar in the Dog Fence Industry

Congratulations on your purchase of a Pet Stop EcoLite™, Rechargeable Receiver. For best results, please read this Guide and all accompanying information. If you have any questions, please contact Mike Sinteff (404)536-6770.

Precautions

DO NOT use this product for guard dogs or vicious animals. If you believe your dog may pose a threat to others, **DO NOT USE THIS PRODUCT PLEASE GIVE MIKE SINTEFF A CALL AT 404-536-6770 TO DISCUSS YOUR OPTIONS**

DO NOT use this product as solid barrier. The product is meant to train pets to remain within an established boundary. It will not work without proper training.

DO NOT permit children to use this product.

Additionally, the product will not work unless you:

- Adjust the collar snug enough for the probes to make contact with your pet's skin, but not so tight that it will cause injury.
- Recharge the battery whenever you see the red blinking light or monthly, whichever is sooner. The charge last 4-6 weeks
- Train your pet properly, if you have any questions containment, please give Mike Sinteff a call (404)536-6770



To avoid neck irritation, always remove the receiver collar from your pet at the end of the day when your pet is inside. Check your pet's neck frequently for any irritation. If irritation occurs, discontinue using the product until the irritation clears up. Put the collar out of reach so you dog does not chew the collar.



To avoid breaking your EcoLite Receiver, do not over tighten screw your cap beyond the flange after charging. Be careful not to cross thread your cap as you screw it in flush with the flange. Recharge every 4-6 weeks. Please give Mike Sinteff a call at (404)536-6770 with questions or concerns

Product Description

The EcoLite is a small and rechargeable receiver. It is molded in a translucent Lexan plastic, known to be a tough and durable plastic. This product is designed to be compatible with all Invisible Fence 800 Series Transmitters and is the lightest (at $\frac{3}{4}$ ounce) and smallest physical size in the Electronic Dog Fence Industry. This is the only Rechargeable Commercial Dog Collar in the Dog Fence Industry.

The translucent nature of the case allows you to see various lights that are incorporated within the receiver itself. These lights include:

- **A blinking red light, to alert you that the battery requires charging.**
- **A solid green light that lets you know the unit is charging**
- **A blinking white light, which can be activated with the optional White Light Activator. The White Light is used to help dog owners see their dog in low light conditions or at night.**

The EcoLite incorporates additional security features to guard against false activations. Pet Stop's unique DM Modulation is Fast and Accurate so there is never any confusion as to when it should activate perfectly. Also, the signal detection scheme is as fast as or faster than any other product currently on the market. The EcoLite receiver incorporates three antennas to be Omni-directional locating the dog in its yard 100% of the time. This technologically advance collar is also fitted with a safety shut-off should there is ever be a time that the dog becomes trapped in his fence.

Charging the Receiver – 25 year battery

Included with the EcoLite is a plug-in wall charger, a small Allen wrench and a spare screw cap. The charger is used to charge the internal rechargeable battery of the EcoLite receiver. The Allen wrench is used to remove the protective cap to expose the charging port. The spare cap is provided in case you lose the protective charging cap.

To charge the EcoLite, simply use the Allen wrench to remove the protective cap covering the charging port. Plug the charger into any service outlet and the charging port into the EcoLite receiver. When inserting the charging port, push gently until you feel a 'click'. When the EcoLite is charging, a solid green light can be seen through the EcoLite case. When fully charged, the solid green light will turn off. Be very careful not to over tighten the cap or cross thread the cap when tightening.

The Optional Light Activator

Position the optional White light Activator to within about 6 to 16 inches of the EcoLite Receiver and press the button on the Activator. The White Light should begin blinking about every 6 seconds. To deactivate the light, again position optional White Light Activator to within about 6 to 16 inches of the EcoLite receiver and press the button on the Activator. (The EcoLite will blink three times before shutting off). We recommend using the White Light Feature for limited periods to conserve the battery.

To change the battery, remove the three screws on the back of the Activator and replace the battery using a 2450 lithium cell.